


CJX2(LC1-D)AC Contactor




CJX2-09(LC1-D09)
CJX2-12(LC1-D12)



CJX2-18(LC1-D18)
CJX2-25(LC1-D25)




CJX2-32(LC1-D32)




CJX2-40(LC1-D40)

Application

CJX2 series AC Contactor is suitable for using in the circuits the rated voltage up to 660V AC 50Hz or 60 Hz, rated current up to 95A, for making & breaking, frequently starting & controlling the AC motor. Combined with the auxiliary contact block, timer delay & machine- interlocking device etc, it becomes the delay contactor, mechanical interlocking contactor, star-delta starter. With the thermal relay, it is combined into the electromagnetic starter. The Contactor is produced according to IEC 60947-4, GB14048-4.



CJX2-50(LC1-D50)
CJX2-65(LC1-D65)



CJX2-80(LC1-D80)
CJX2-95(LC1-D95)



New type
CJX2-18N(LC1-D18N)



New type
CJX2-32N(LC1-D32N)

Standard control circuit voltages

Volts	24	42	48	110	220	230	240	380	400	415	440	500	660
50Hz	B5	D5	E5	F5	M5	P5	U5	Q5	V5	N5	R5	S5	Y5
60Hz	B6	D6	E6	F6	M6	-	U6	Q6	—	—	R6	—	—
50/60Hz	B7	D7	E7	F7	M7	P7	U7	Q7	V7	N7	R7	—	—

Specifications

Type		CJX2-09 (LC1-D09)	CJX2-12 (LC1-D12)	CJX2-18 (LC1-D18)	CJX2-25 (LC1-D25)	CJX2-32 (LC1-D32)	CJX2-40 (LC1-D40)	CJX2-50 (LC1-D50)	CJX2-65 (LC1-D65)	CJX2-80 (LC1-D80)	CJX2-95 (LC1-D95)
Rated working current (A)	AC3	9	12	18	25	32	40	50	65	80	95
	AC4	3.5	5	7.7	8.5	12	18.5	24	28	37	44
AC3 capacity of three-phase squirrel-cage motor	220/230V	2.2	3	4	5.5	7.5	11	15	18.5	22	25
	380/400V	4	5.5	7.5	11	15	18.5	22	30	37	45
	415V	4	5.5	9	11	15	22	25	37	45	45
	440V	4	5.5	9	11	15	22	30	37	45	45
AC3(KW)	500V	5.5	7.5	10	15	18.5	22	30	37	55	55
	660/690V	5.5	7.5	10	15	18.5	30	33	37	45	45
Rated heat current(A)		20	20	32	40	50	60	80	80	125	125
Electrical life	AC4 × 10 ⁴	20	20-15	20-7	15-7	15-7	10-7	7	7-6	7-5	7-5
	AC3 × 10 ⁶	2	2	2	2	2	2	2	1.6	1.6	1.6
Mechanical life × 10 ⁶		20	20	20	20	20	20	50	20	10	10
Number of the contact		3P+NO									
		3P+NC									